



COB PAR 200
RGBW 4IN1 COB LED



User Manual

Caution!

Please read the instruction carefully before use

Be careful with your operations. With a dangerous voltage you can suffer a dangerous electric shock when touching the wires!

Keep this device away from rain and moisture!

Make sure it is grounded when using it!

Unplug mains lead before opening the housing!

For your own safety, please read this user manual carefully before you initial start-up.

Introduction

Thank you for having chosen this Item. You will see you acquired a powerful and versatile device. Unpack your item. Before you initial start-up, please make sure that there is no damage caused by transportation. Should there be any, consult your dealer and do not use the device.

Safety instructions

This device has left our premises in absolutely perfect condition. In order to maintain this condition and to ensure a safe operation, it is absolutely necessary for the user to follow the safety instructions and warning notes written in this user manual. Always disconnect from the mains, when the device is not in use or before cleaning it. Keep away children and amateurs from the device! There are no serviceable parts inside the device.

Specifications

Input power:AC100-240V 50/60 Hz

Power consumption:200w

LED:1 pcs 200W (4-in-1) COB

light distribution uniform and soft

DMX channel:4/8 channels

Beam angle:60 degree

Temperature control protection

Control mode: DMX512/Master-Slave/Auto run/sound

0-100% linear dimmer

high speed synchronous strobe

IP-Rating: IP20


product size : 230×280×350mm

packing size : 255×255×360mm

N.W : 3.5Kg

G.W : 4.3KG

Control menu



[MENU] Main menu to select or return to the previous menu

[UP] Menu selection or parameter increase

[DOWN] Menu selection or parameter decrease

[ENTER] OK / enter or select sub menu

Show	Value	Function
STAT	R.000-255	Static colour mode, Red dimmer ,dark to bright
	G.000-255	Static colour mode, Green dimmer ,dark to bright
	B.000-255	Static colour mode, Blue dimmer ,dark to bright
	W.000-255	Static colour mode, White dimmer ,dark to bright
CC.00	CC.00-99	Colour change mode
CP.00	CP.00-99	Colour fade mode
dE.00	dE.00-99	Auto mode
bEbE		Sound control
CHAN	CH.04	4 channel
	CH.08	8 channel
d.001	d.001-512	DMX setting

Channel modes:

4 channel mode

4-CHANNEL-MODE			
Channel	Function	Values	Function
1	Red	0-255	Dimmer 0 - 100%
2	Green	0-255	Dimmer 0 - 100%
3	Blue	0-255	Dimmer 0 - 100%
4	White	0-255	Dimmer 0 - 100%

8 channel mode

8-CHANNEL-MODE			
Channel	Function	Values	Function
1	Master Dimmer	0-255	Dimmer 0 - 100%
2	Multifunctional Strobe	0-10	Strobe open
		11-255	Strobe slow -> fast (1Hz - 20Hz)
3	no Function	0-49	Color Macro
	Colour change	50-99	
	Colour fade	100-149	
	Colour fade in/out	150-199	
	Sound active	200-255	
4	Chase/fade speed (slow to fast)	0-255	
5	Red	0-255	Dimmer 0 - 100%
6	Green	0-255	Dimmer 0 - 100%
7	Blue	0-255	Dimmer 0 - 100%
8	White	0-255	Dimmer 0 - 100%

Set DMX address

Display the DMX 512 value of each channel. With this function you can display the DMX 512 value of each channel. The display automatically shows the channel with a value changing.