




FOS PAR Aurora



Version 1.0

USER MANUAL

- Be sure to read the USER MANUAL carefully before using this product.
- Be sure to keep the USER MANUAL properly for future needs.
- Use this product correctly when you can fully understand the User Manual

1.Safety instructions

Thank you for choosing our FOS PAR Aurora. FOR YOUR OWN SAFETY, PLEASE READ THIS USER MANUAL CAREFULLY

BEFORE YOU INITIAL START - UP!

CAUTION!
Be careful with your operations.
With a high voltage you can suffer a dangerous electric shock when touching the wires!

This device has left our premises in absolutely perfect condition. In order to maintain this condition and to ensure a safe operation, it is absolutely necessary for the user to follow the safety instructions and warning notes written in this manual.

CAUTION!
Keep this device away from rain and moisture!
Unplug mains lead before opening the housing!

Important:

The manufacturer will not accept liability for any resulting damages caused by the non-observance of this manual or any unauthorized modification to the device.

Please consider that damages caused by manual modifications to the device are not subject to warranty.

During the operation the housing becomes hot). Allow the fixture to cool approximately 20 minutes prior to manipulate with it.

Make sure that the available voltage is not higher than stated on the rear panel.

WARNING! This unit does not contain an ON/OFF switch. Always disconnect power input cable to completely remove power from unit when not in use or before cleaning or servicing the fixture.

Make sure that the power-cord is never crimped or damaged by sharp edges. Check the device and the power-cord from time to time.

Always disconnect from the mains, when the device is not in use or before cleaning it. Only handle the power-cord by the plug. Never pull out the plug by tugging the power cord.

This device falls under protection class I. Therefore it is essential to connect the yellow/green conductor to earth.

The electric connection, repairs and servicing must be carried out by a qualified employee.

Do not connect this device to a dimmer pack.

Do not switch the fixture on and off in short intervals as this would reduce the lamp's life.

During the initial start-up some smoke or smell may arise. This is a normal process and does not necessarily mean that the device is defective.

Do not touch the device's housing bare hands during its operation (housing becomes hot)!

For replacement use lamps and fuses of same type and rating only.

CAUTION ! EYE DAMAGES !
Avoid looking directly into the light source
(meant especially for epileptics) !

10.Maintenance and cleaning

It is absolutely essential that the fixture is kept clean and that dust, dirt and smoke-fluid residues must not build up on or within the fixture. Otherwise, the fixture's light-output will be significantly reduced. Regular cleaning will not only ensure the maximum light-output, but will also allow the fixture to function reliably throughout its life. A soft lint-free cloth moistened with any good glass cleaning fluid is recommended, under no circumstances should alcohol or solvents be used!

DANGER !
Disconnect from the mains before starting any
maintenance work

The front objective lens will require weekly cleaning as smoke-fluid tends to building up residues, reducing the light-output very quickly. The cooling-fans should be cleaned monthly.

The interior of the fixture should be cleaned at least annually using a vacuum-cleaner or an air-jet. Dichroic colour filters, CMY lamellas, gobo and graphic wheels and the internal lenses should be cleaned monthly. Remove dust and dirt from the fans and cooling vents using a soft brush and vacuum-cleaner.

Important! Check the air filters periodically and clean before they become clogged!

Clean two air filters placed in the fixture's covers and two in the fixture base. Use a vacuum cleaner, compressed air or you can wash them and put back dry.

After replacing the air filters, reset the elapsed time counter in the menu "Information" (Information--->Air Filters--->Elapsed Time).


Replacing the fuse. Before replacing the fuse, unplug mains lead.

- 1) Remove the fuse holder on the rear panel of the base with a fitting screwdriver from the housing (anti-clockwise).
- 2) Remove the old fuse from the fuse holder.
- 3) Install the new fuse in the fuse holder (only the same type and rating).
- 4) Replace the fuseholder in the housing and fix it.

9	7	0..15	Macro RUN
		16..31	No function
		32..47	Macro Run 1
		48..63	Macro Run 2
		64..79	Macro Run 3
		80..95	Macro Run 4
		96..111	Macro Run 5
		112..127	Macro Run 6
		128..143	Macro Run 7
		144..159	Macro Run 8
		160..175	Macro Sound 1
		176..191	Macro Sound 2
		192..207	Macro Sound 3
		208..223	Macro Sound 4
		224..239	Macro Sound 5
		240..255	Macro Sound 6
10	8	0..255	Macro Speed
11	9	0..255	Macro Speed from Slow To Fast
12		0..255	Pix_Dimmer
		0..255	Pix_Dimmer 0%...100%
13		0..255	Pix_Red
		0..255	0-100% Pix_Red dimmer from dark to bright
14		0..255	Pix_Green
		0..255	0-100% Pix_Green dimmer from dark to bright
15		0..255	Pix_Blue
		0..255	0-100% Pix_Blue dimmer from dark to bright
15	10	0..0	Pix_color
		1..15	No Function
		16..31	Red
		32..47	Green
		48..63	Blue
		64..79	Red+Blue
		80..95	Red+Green
		96..111	Green+Blue
		112..127	Red+Blue+Green
		128..143	2700K
		144..159	3200K
		160..175	3500K
		176..191	5000K
		192..207	5500K
		208..223	6000K
		224..239	6500K
		240..255	7000K
16	11	0..15	Pix_Macro
		16..29	No Function
		30..43	Pix Dynamic Scene1
		44..57	Pix Dynamic Scene2
		58..71	Pix Dynamic Scene3
		72..85	Pix Dynamic Scene4
		86..99	Pix Dynamic Scene5
		100..113	Pix Dynamic Scene6
		114..127	Pix Dynamic Scene7
		128..143	Pix Dynamic Scene8
		144..159	Pix Dynamic Scene9
		160..175	Pix Dynamic Scene10
		176..191	Pix Dynamic Scene11
		192..207	Pix Dynamic Scene12
		208..223	Pix Dynamic Scene13
		224..239	Pix Dynamic Scene14
		240..255	Pix Dynamic Scene15
16	11	226..239	Pix Dynamic Scene16
		240..255	Pix Dynamic Scene17
17	12	0..255	Pix_Macro_Speed
		0..255	Slow to Fast

2.UNPACKING

FOS PAR Aurora adopts a 7 x 12W 4-IN-1 RGBW LEDs & 60 x 0.2W RGB LEDs which features high brightness and stability. Please carefully unpack it when you receive the fixture and check whether it is damaged during the transportation. And please check whether the following items are included inside the box:



FOS PAR Aurora is made of a new type of high temperature strength of engineering plastics and cast aluminum casing with nice outlook . The fixture is designed and manufactured strictly following CE standards, complying with international standard DMX512 protocol. It's available independently controlled and linkable with each other for operation. And it is applicable for large-scale live performances, theater, studio, nightclubs and discos.

This manual covers the important information on installation and applications. Meanwhile, please keep this manual well for future needs.


3.TECHNICAL INFORMATION

SPECIFICATIONS :

- Powered by 7 x 12W 4-IN-1 RGBW LEDs & 60 x 0.2W RGB LEDs
- Input Voltage: AC90-260V 50-60Hz
- Power Consumption: 90W
- Built-in Neon light effect
- Full LED controllable
- IR remote
- Control Signal:DMX512, master-slave and sound activated
- Control Channel: 17/12 DMX Channels USITT DMX-512
- Dimensions: 265(D)*117(W)*213(H)mm
- Packing Dimensions: 280(D)*245(W)*150(H)mm
- Net Weight: 2.18kgs
- Gross Weight: 3kgs

FEATURES:


- 50,000 hours life span and low power consumption
- Cooling system
- CTB and CTO,linear colour temperature 2800K-8000K changable
- 16.7million additive RGBW colors whit full saturation control
- Built-in programs that could be called up via a DMX controller
- 25t/s strobe effect and pulse strobe effect
- 0-100% electronic dimming
- 4-button LED display on rear panel
- POWERCON connector IN/OUT
- 3-Pin XLR connectors IN/OUT
- Overheat protection
- -35 ° C ~ 45 ° C max ambient temperature



9.DMX PROTOCOL


Mode/Channel		Value	Function
CH17	CH12		
1	1		Dimmer
		0..255	Dimmer 0%...100%
2	2		Shutter
		0..31	Shutter closed
		32..63	shutter open
		64..95	Strobe effect slow to fast
		96..127	shutter open
		128..159	Pulse-effect in sequences slow to fast
		160..191	shutter open
		192..223	Random strobe effect slow to fast
		224..255	shutter open
3	3		Red
		0..255	0-100% Red dimmer from dark to bright
4	4		Green
		0..255	0-100% Green dimmer from dark to bright
5	5		Blue
		0..255	0-100% Blue dimmer from dark to bright
6	6		White
		0..255	0-100% White dimmer from dark to bright
7			Macro Color
		0..15	No Function
		16..31	Red
		32..47	Green
		48..63	Blue
		64..79	White
		80..95	Red+Green
		96..111	Red+Blue
		112..127	Red+White
		128..143	Green+Blue
		144..159	Green+White
		160..175	Blue+White
		176..191	R+G+B
		192..207	R+G+B+W
		208..212	2700K
		213..217	3200K
		218..222	3500K
		223..227	5000K
		228..232	5500K
		233..237	6000K
		238..242	6500K
		243..247	7000K
		248..255	8000K
8			Color Temp
		0..15	No Function
		16..45	Below 3200K
		46..75	3200K - 3500K
		76..105	3500K - 5000K
		106..135	5000K - 5500K
		136..165	5500K - 6000K
		166..195	6000K - 6500K
		196..225	6500K - 7000K
		226..255	7000K - 8000K

8.MENU OPERATIONS



MENU				Description
MODE	ADDR	VALU	A001~A XXX (A XXX)	DMX address setting
		SLAV		Standalone mode
	AUTO	IP1~8	ALON /(AU -A)	SP_1~ SP_5 (Speed)
			MAST /(A U-M)	SP_1~ SP_5 (Speed)
	SOUN	IP1~7	ALON (SO-A)	Sound control(Alone)
			MAST (SO -M)	Sound setting(Master)
SET	MIC	M-XX		Mic sensitivity setting
	LODA	ON/ OFF		Reload data
	VER	V-2.0		Software version
	CALI	Code (Password: 088)		Input password
		CH03—CH06		Calibration
	SSET	WD		Wire DMX input
DMX	MOD1			17CH
	MOD2			12CH
REST	ON/ OFF			Total reset
TEST	CXXX		000-255	Manual channel control
TEMP	TXXX			Current temperature

4.PHOTOMETRICS DIAGRAM



5.OPERATION INSTRUCTIONS

- FOS PAR Aurora is for wash effect for on-site decoration purpose.
- Don't turn on the fixture if it's been through severe temperature difference like after transportation because it might damage the light due to the environment changes. So make sure to operate the fixture until it is in normal temperature.
- This light should be keep away from strong shaking during any transportation or movement.
- Don't pull up the light by only the head, or it might cause damages to the mechanical parts.
- Don't expose the fixture in overheat, moisture or environment with too much dust when installing it. And
- don't lay any power cables on the floor. Or it might cause electronic shock to the people.
- Make sure the installation place is in good safety condition before installing the fixture.
- Make sure to put the safety chain and check whether the screws are screwed properly when installing the fixture.
- Make sure the lens are in good condition.It's recommended to replace the units if there are any damages or severe scratch.
- Make sure the fixture is operated by qualified personnel who knows the fixture before using.
- Keep the original packages if any second shipment is needed.
- Don't try to change the fixtures without any instruction by the manufacturer or the appointed repairing agencies.
- It is not in warranty range if there are any malfunctions from not following the user manual to operate or any illegal operation, like shock short circuit, electronic shock , lamp broke, etc.

6.INSTALLATIONS

Cautions:

For added protection mount the fixtures in areas outside walking paths, seating areas, or in areas where the fixture might be reached by unauthorized personnel.

Before mounting the fixture to any surface, make sure that the installation area can hold a minimum point load of 10 times the device's weight.

Fixture installation must always be secured with a secondary safety attachment, such as an appropriate safety cable.

Never stand directly below the device when mounting, removing, or servicing the fixture.

from a ceiling, or set on a flat level surface (see illustration below). Be sure this fixture is kept at least 0.5m (1.5 ft) away from any flammable materials (decoration etc.).

Always use and install the supplied safety cable as a safety measure to prevent accidental damage and/or injury in the event the clamp fails.


Mounting points:

Overhead mounting requires extensive experience, including amongst others calculating working load limits, a fine knowledge of the installation material being used, and periodic safety inspection of all installation material and the fixture. If you lack these qualifications, do not attempt the installation yourself. Improper installation can result in bodily injury.


Be sure to complete all rigging and installation procedures before connecting the main power cord to the appropriate wall outlet.

Clamp Mounting:

The FOS PAR Aurora provides a unique mounting bracket assembly that integrates the bottom of the base, and the safety cable rigging point in one unit (see the illustration below). When mounting this fixture to truss be sure to secure an appropriately rated clamp to the included omega bracket using a M10 screw fitted through the center hole of the handle. As an added safety measure be sure to attach at least one properly rated safety cable to the fixture using one of the safety cable rigging points integrated in the base assembly.



7.CONTROL CONNECTION



Connect the provided XLR cable to the female 3-pin XLR output of your controller and the other side to the male 3-pin XLR input of the moving head. You can chain multiple Moving head together through serial linking. The cable needed should be two core, screened cable with XLR input and output connectors. Please refer to the diagram below. DMX-512 connection with DMX terminator.

For installations where the DMX cable has to run a long distance or is in an electrically noisy environment, such as in a discotheque, it is recommended to use a DMX terminator. This helps in preventing corruption of the digital control signal by electrical noise. The DMX terminator is simply an XLR plug with a 3 resistor connected between pins 2 and 3, which is then plugged into the output XLR socket of the last fixture in the chain. Please see illustrations below.

